

## Main Features

---

MIDI Control Full assignable MIDI controls

---

ProDJ Link Yes

---

P-LOCK Fader Caps Yes

---

Auto Standby Yes

---

Compatible DJ Software rekordbox

---

DVS Control

- rekordbox dvs ready (not included)
- Paid upgrade to Serato DJ Essentials

---

What's in the box

- DJM-900NXS2
- Power cord
- USB cable
- Operating Instructions (Quick Start Guide)

---

## Specifications

---

Sampling Rate 96 kHz

---

---

Width 13.11 in

---

Height 4.25 in

---

Depth 16.31 in

---

Weight 17.64 lb

---

Frequency Range 20 - 40000 Hz

---

A/D Converter 24 bit

---

D/A Converter 32 bit

---

S/N Ratio Line 105 dB

---

S/N Ratio Phono 88 dB

---

S/N Ratio Mic 79 dB

---

Distortion < 0.005 % (LINE)

## Channels

---

EQ/ISO

3 band

---

EQ/ISO Range

Built-in, switchable 3-band equaliser: -26 dB ~ +6 dB /  
3-band isolator:  $-\infty$  ~ +6 dB

## Performance Control

---

Channels

4

---

Sound Color FX

- Crush
  - Dub Echo
  - Filter
  - Noise
  - Sweep
  - Space
-

---

Beat FX

- Delay
- Echo
- Filter
- Flanger
- Helix
- Phaser
- Ping Pong
- Pitch
- Slip Roll
- Spiral
- Reverb
- Roll
- Trans
- Vinyl Brake

---

FX Frequency

Yes

---

X-PAD

Yes

---

rekordbox Quantize

Yes

## **Crossfader**

---

Crossfader Type

Magvel Fader

---

CURVE Assignable

Yes

---

---

Fader Curve 3

## Mic

---

Mic Connection

- XLR / 1/4-inch Jack Combo
- 1/4-inch TRS Jack

---

Talkover 3 Position Switch

---

Talkover Attenuator Yes

## Terminals

---

Inputs

- 4 DIGITAL (Coaxial)
- 4 CD/LINE (RCA)
- 4 PHONO (RCA)
- 2 MIC (XLR/TRS Jack Combo, 1/4 inch TRS Jack)

---

Send/Return

- 1 SEND (1/4-inch TS jack)
- 1 RETURN (1/4-inch TS jack)

---

LAN 1

---

---

USB

- 2 USB B ports
- 1 USB A port

---

Outputs

- 2 MASTER (XLR, RCA)
- 1 BOOTH (1/4 inch TRS Jack)
- 2 HEADPHONE MONITOR (1/4 inch Jack, mini-jack)
- 1 REC OUT (RCA)
- 1 DIGITAL (Coaxial)